



### Standard Jamma Pinout

Parts Side		Solder Side	
GND	1	A	GND
GND	2	B	GND
+5V	3	C	+5V
+5V	4	D	+5V
-5V	5	E	-5V
+12V	6	F	+12V
Key	7	H	Key
Coin Meter 1	8	J	Coin Meter 2
Coin Lockout 1	9	K	Coin Lockout 2
Speaker +	10	L	Speaker -
N/C	11	M	N/C
Video Red	12	N	Video Green
Video Blue	13	P	Video Sync
Video Ground	14	R	Service
Test	15	S	Tilt
Coin 1	16	T	Coin 2
P1 Start	17	U	P2 Start
P1 Up	18	V	P2 Up
P1 Down	19	W	P2 Down
P1 Left	20	X	P2 Left
P1 Right	21	Y	P2 Right
P1 S1	22	Z	P2 S1
P1 S2	23	a	P2 S2
P1 S3	24	b	P2 S3
P1 S4	25	c	P2 S4
N/C	26	d	N/C
GND	27	e	GND
GND	28	f	GND